

TIA/EIA TIA/EIA T568A DESIGNATIONS White/Orange White/Gree Green Orange White/Orang White/Green (1) Product accessories Blue Blue White/Blu White/Blue Orange Green White/Brown Brown Part 1: 5.5-8.5 mm Copper foil paper **2** 2.1 Insert the network 2.2 Peel off the cover of the cable into the nut 1.2-inch network cable from the end 2.4 2.3 Fold back braid Wrap a layer of and drain wire copper foil Copper foil paper $(\mathbf{3})$ Fan out all four twisted pairs, following the color coding label and allocate each conductor into proper slots on wiring cap. Trim the ends of conductors. Wiring label Tear off excess stickers Place wiring cap on plug (6) Place the wiring cap onto plug, use plier to clamp wiring cap until it completely along the dotted line snaps-in to effect the connection Close the plug cover, make sure the power cord makes proper contact with the ground clip on the plug, and tighten the nut